

WIRELESS COMMUNICATION NETWORK WITH TRACKING DISH ANTENNA

The present invention relates to multiple beam antennas and specifically to such antenna used in communication systems. This application is a continuation-in-part application of Serial No. 09/847,629 filed May 2, 2001, Serial No. 09/872,542 filed June 2, 2001, Serial No. 09/872,621 filed June 2, 2001, Serial No. 09/882,482 filed June 14, 2001, Serial No. 09/952,591, filed September 14, 2001, and Serial No. 09/965,875 filed September 28, 2001, all of which are incorporated herein by reference.

BACKGROUND OF THE INVENTION

Wireless Communication

Point-to-Point and Point-to-Multi-Point

Wireless communications links, using portions of the electromagnetic spectrum, are well known. Most such wireless communication at least in terms of data transmitted is one way, point to multi-point, which includes commercial radio and television. However there are many examples of point-to-point wireless communication. Mobile telephone systems that have recently become very popular are examples of low-data-rate, point-to-point communication. Microwave transmitters on telephone system trunk lines are another example of prior art, point-to-point wireless communication at much higher data rates. The prior art includes a few examples of point-to-point laser communication at infrared and visible wavelengths.

Need for High Volume Information Transmission

8.12.6
9/15/04
The need for faster ^{i.e.} ~~(i.e.)~~ higher volume per unit time) information transmission is growing rapidly. Today and into the foreseeable future transmission of information is and will be digital with volume measured in bits per second. To transmit a typical telephone conversation digitally utilizes about 5,000 bits per second (5 Kbits per second). Typical personal computer modems connected to the Internet operate at, for example, 56 Kbits per second. Music can be transmitted point to point in real time with good quality using mp3 technology at digital data rates of 64 Kbits per second. Video can be

transmitted in real time at data rates of about 5 million bits per second (5 Mbits per second). Broadcast quality video is typically at 45 or 90 Mbps. Companies (such as telephone and cable companies) providing point-to-point communication services build trunk lines to serve as parts of communication links for their point-to-point customers. These trunk lines typically carry hundreds or thousands of messages simultaneously using multiplexing techniques. Thus, high volume trunk lines must be able to transmit in the gigabit (billion bits, Gbits, per second) range. Most modern trunk lines utilize fiber optic lines. A typical fiber optic line can carry about 2 to 10 Gbits per second and many separate fibers can be included in a trunk line so that fiber optic trunk lines can be designed and constructed to carry any volume of information desired virtually without limit. However, the construction of fiber optic trunk lines is expensive (sometimes very expensive) and the design and the construction of these lines can often take many months especially if the route is over private property or produces environmental controversy. Often the expected revenue from the potential users of a particular trunk line under consideration does not justify the cost of the fiber optic trunk line. Digital microwave communication has been available since the mid-1970's. Service in the 18-23 GHz radio spectrum is called "short-haul microwave" providing point-to-point service operating between 2 and 7 miles and supporting between four to eight T1 links (each at 1.544 Mbps). Recently, microwave systems operation in the 11 to 38 GHz band have reportably been designed to transmit at rates up to 155 Mbps (which is a standard transmit frequency known as "OC-3 Standard") using high order modulation schemes.

Data Rate vs Frequency

Bandwidth-efficient modulation schemes allow, as a general rule, transmission of data at rates of 1 to 10 bits per Hz of available bandwidth in spectral ranges including radio wave lengths to microwave wavelengths. Data transmission requirements of 1 to tens of Gbps thus would require hundreds of MHz of available bandwidth for transmission. Equitable sharing of the frequency spectrum between radio, television, telephone, emergency services, military and other services typically limits specific frequency band allocations to about 10% fractional bandwidth (i.e., range of frequencies equal to about 10% of center frequency). AM radio, at almost 100% fractional bandwidth (550 to 1650 kHz) is

an anomaly; FM radio, at 20% fractional bandwidth, is also atypical compared to more recent frequency allocations, which rarely exceed 10% fractional bandwidth.

Reliability Requirements

Reliability typically required for wireless data transmission is very high, consistent with that required for hardwired links including fiber optics. Typical specifications for error rates are less than one bit in ten billion (10^{-10} bit-error rates), and link availability of 99.999% (5 minutes of down time per year). This necessitates all-weather link operability, in fog and snow, and at rain rates up to 100 mm/hour in many areas.

Weather Conditions

In conjunction with the above availability requirements, weather-related attenuation limits the useful range of wireless data transmission at all wavelengths shorter than the very long radio waves. Typical ranges in a heavy rainstorm for optical links (i.e., laser communication links) are 100 meters and for microwave links, 10,000 meters.

Atmospheric attenuation of electromagnetic radiation increases generally with frequency in the microwave and millimeter-wave bands. However, excitation of rotational transitions in oxygen and water vapor molecules absorbs radiation preferentially in bands near 60 and 118 GHz (oxygen) and near 23 and 183 GHz (water vapor). Rain, which attenuates through large-angle scattering, increases monotonically with frequency from 3 to nearly 200 GHz. At the higher, millimeter-wave frequencies, (i.e., 30 GHz to 300 GHz corresponding to wavelengths of 1.0 millimeter to 1.0 centimeter) where available bandwidth is highest, rain attenuation in very bad weather limits reliable wireless link performance to distances of 1 mile or less. At microwave frequencies near and below 10 GHz, link distances to 10 miles can be achieved even in heavy rain with high reliability, but the available bandwidth is much lower.

Communication Antennas

Low Frequencies

At frequencies below ~~about~~ below 3 GHz, antennas of practical size are nearly omnidirectional, so beams from different antennas interfere, and the only equitable way to share the airwaves is by parceling the frequency spectrum. Licenses for a given spectrum band are auctioned to a single service provider in each geographical area, thereby eliminating competition in that area. To guarantee efficient use of the spectrum, bandwidth efficiency is mandated in this range of the radio spectrum.

Higher Frequencies

At higher frequencies from about 3 to 60 GHz, antenna beams become somewhat directional, so beam interference can be avoided spatially. Here point-to-point licenses may be granted for services overlapping in frequency but not in space, or for services overlapping in space but not in frequency. The two-dimensional coordination afforded in this spectral range increases the number of licensees who can coexist in a given geographical area, allowing for increased competition.

Millimeter Wave Frequencies

At frequencies above 60 GHz to about 130 GHz, antennas of practical size can generate highly directional "pencil beams" which do not interfere at all, because of their extremely limited spatial extent. A typical dish antenna of two-foot diameter operating at 94 GHz projects a half-power beam width of 0.36 degrees providing a gain of about ^{51 dB}~~51 dB~~. (Gain is the ratio of the radiation intensity in a desired direction to the total input power accepted at an input port of the antenna. The ratio is usually expressed in decibels.)

Dish Antennas

Most antennas used for high-gain applications utilize a large parabolic primary collector in one of a variety of geometries. In a prime-focus antenna the receiver is placed directly at the focus of the parabola. In a Cassegrain antenna a convex hyperboloidal secondary reflector is placed in front of the focus to reflect the focus back through an aperture in the primary to allow mounting the receiver behind the dish. (This is convenient since the dish is typically supported from behind as well.) An offset parabola rotates the focus

away from the center of the dish for less aperture blockage and improved mounting geometry.

The required surface tolerance on the dish of a high quality conductive parabola antenna is about 15 thousandths of an inch (15 mils) for microwave applications (below 40 GHz), but closer to 5 mils for MMW communications (57-100 GHz). Molded composites have achieved 5-mil tolerances, but are inherently quite expensive. Typical hydroformed aluminum dishes are inexpensive but cannot achieve adequate surface tolerances for MMW applications. The secondary reflector in the Cassegrain geometry is a small, machined aluminum "lollipop" which can be made to 1-mil tolerance without difficulty. Mounts for secondary reflectors and receiver waveguide horns preferably comprise mechanical fine-tuning adjustment for in-situ alignment on an antenna test range.

Coarse and Fine Pointing

Pointing a high-gain antenna requires coarse and fine positioning. Coarse positioning can be accomplished initially using a visual sight such as a bore-sighted rifle scope or laser pointer. The antenna is typically locked in its final coarse position prior to fine-tuning. The fine adjustment is performed with the remote transmitter turned on. A power meter connected to the receiver is monitored for maximum power as the fine positioner is adjusted and locked down. Any subsequent unintended displacement and/or rotation of the antenna due to thermal effects, wind loading, or any other external force will cause the antenna beam to wander off of the remote transmitter.

Prior Art Tracking Antennas

In a Cassegrain antenna, a rotating, slightly off-axis feed horn ("conical scan") steers the beam mechanically without moving the large primary dish. For Cassegrain, prime focus or offset parabola antennas, a multi-aperture feed (e.g. quad-cell) could be used with a selectable switching array or a monopulse transceiver. In these dish architectures, beam tracking is based upon maximizing signal power or minimizing wave front tilt into the receiver. In all cases, using a common aperture or mounting structure for the receiver and transmitter antennas ensures that the transmitter is correctly pointed along with the

Ref. 6
9/10/04

receiver. Flat panel antennas are also used for tracking and have been used extensively for radar tracking. One example is a flat-panel phased array, antenna with a Rotman lens. In this antenna phased array beam combining from multiple output ports of the Rotman lens is used to steer the beam azimuthally over many antenna beam widths without mechanically rotating the antenna itself.

Trunk Lines

Trunk lines typically carry hundreds or thousands of messages simultaneously using multiplexing techniques. Thus, high volume trunk lines must be able to transmit in the gigabit (billion bits, Gbits, per second) range. Most modern trunk lines utilize fiber optic lines. A typical fiber optic line can carry about 2 to 10 Gbits per second and many separate fibers can be included in a trunk line so that fiber optic trunk lines can be designed and constructed to carry any volume of information desired virtually without limit. However, the construction of fiber optic trunk lines is expensive (sometimes very expensive) and the design and the construction of these lines can often take many months especially if the route is over private property or produces environmental controversy. Often the expected revenue from the potential users of a particular trunk line under consideration does not justify the cost of the fiber optic trunk line.

The Need

A need exists for a complete wireless communication networks which can be put into place quickly and efficiently to provide high data rate information service to a service region independent of and in competition with existing local services where local services already exists or to provide high data rate communication service in regions where such services ^{do not} ~~no not~~ now exists. Such systems would need narrow beam width high-data-rate, high-frequency communication antennas with facilities for keeping the antennas aligned permitting the utilization of the same frequency bands over and over again to provide trunk line connections between base stations and connections with larger communication networks.

2/15/29

SUMMARY OF THE INVENTION

6-1-6
9/15/04

The present invention provides a point-to-point, wireless, millimeter wave communications links equipped with tracking antennas to maintain pencil beam contact between the links. In a preferred embodiment the communication links operate within the 92 to 95 GHz portion of the millimeter spectrum and provides data transmission rates in excess of 155 Mbps. A first transceiver transmits at a first bandwidth and receives at a second bandwidth both within the above spectral range. A second transceiver transmits at the second bandwidth and receives at the first bandwidth. The transceivers are equipped with antennas providing beam divergence small enough to ensure efficient spatial and directional partitioning of the data channels so that an almost unlimited number of transceivers will be able to simultaneously use the same spectrum. In a preferred embodiment the first and second spectral ranges are 92.3-93.2 GHz and 94.1-95.0 GHz and the half power beam width is about 0.36 degrees or less.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic diagram of a millimeter-wave transmitter of a prototype transceiver system built and tested by Applicants.

FIG. 2 is a schematic diagram of a millimeter-wave receiver of a prototype transceiver system built and tested by Applicants.

FIG. 3 is measured receiver output voltage from the prototype transceiver at a transmitted bit rate of 200 Mbps.

FIG. 4 is the same waveform as FIG. 3, with the bit rate increased to 1.25 Gbps.

501, 502
501, 502
FIGS. 5A and 5B are schematic diagrams of a millimeter-wave transmitter and receiver in one transceiver of a portion of a preferred embodiment of the present invention.

Rev. 6, 4/10/04
FIGS. 6A, 6B1, and 6B2

FIG. 6A and 6B are schematic diagrams of a millimeter-wave transmitter and receiver in a complementary transceiver of a portion of a preferred embodiment of the present invention.

FIGS. 7A and 7B show the spectral diagrams for a preferred embodiment of the present invention.

FIG. 8 is a layout showing an installation using a preferred embodiment of the present invention.

FIGS. 9, 10 and 11 describe elements of a preferred embodiment of the present invention.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Prototype Demonstration

A prototype demonstration of the millimeter-wave transmitter and receiver useful for the present invention is described by reference to FIGS. 1 to 4. With this embodiment the Applicants have demonstrated digital data transmission in the 93 to 97 GHz range at 1.25 Gbps with a bit error rate below 10^{-12} .

The circuit diagram for the millimeter-wave transmitter is shown in FIG. 1. Voltage-controlled microwave oscillator 1, Westec Model VTS133/V4, is tuned to transmit at 10 GHz, attenuated by 16 dB with coaxial attenuators 2 and 3, and divided into two channels in two-way power divider 4. A digital modulation signal is pre-amplified in amplifier 7, and mixed with the microwave source power in triple-balanced mixer 5, Pacific Microwave Model M3001HA. The modulated source power is combined with the un-modulated source power through a two-way power combiner 6. A line stretcher 12 in the path of the un-modulated source power controls the depth of modulation of the combined output by adjusting for constructive or destructive phase summation. The amplitude-

modulated 10 GHz signal is mixed with a signal from a 85-GHz source oscillator 8 in mixer 9 and high-pass filtered in wave guide filter 13 to reject the 75 GHz image band. The resultant, amplitude-modulated 95 GHz signal contains spectral components between 93 and 97 GHz, assuming unfiltered 1.25 Gbps modulation. A rectangular WR-10 wave guide output of the high pass filter is converted to a circular wave guide 14 and fed to a circular horn 15 of 4 inches diameter, where it is transmitted into free space. The horn projects a half-power beam width of 2.2 degrees.

The circuit diagram for the receiver is shown in FIG. 2. The antenna is a circular horn 1 of 6 inches in diameter, fed from a waveguide unit 14R consisting of a circular W-band wave-guide and a circular-to-rectangular wave-guide converter which translates the antenna feed to WR-10 wave-guide which in turn feeds heterodyne receiver module 2R. This module consists of a monolithic millimeter-wave integrated circuit (MMIC) low-noise amplifier spanning 89-99 GHz, a mixer with a two-times frequency multiplier at the LO port, and an IF amplifier covering 5-15 GHz. These receivers are available from suppliers such as Lockheed Martin. The local oscillator 8R is a cavity-tuned Gunn oscillator operating at 42.0 GHz (Spacek Model GQ410K), feeding the mixer in module 2R through a 6 dB attenuator 7R. A bias tee 6R at the local oscillator input supplies DC power to receiver module 2R. A voltage regulator circuit using a National Semiconductor LM317 integrated circuit regulator supplies +3.3V through bias tee 5R. An IF output of the heterodyne receiver module 2R is filtered at 6-12 GHz using bandpass filter 3R from K&L Microwave. Receiver 4R which is an HP Herotek Model DTM 180AA diode detector, measures total received power. The voltage output from the diode detector is amplified in two-cascaded microwave amplifiers 5R from MiniCircuits, Model 2FL2000. The baseband output is carried on coax cable to a media converter for conversion to optical fiber, or to a Bit Error-Rate Tester (BERT) 10R.

In the laboratory, this embodiment has demonstrated a bit-error rate of less than 10^{-12} for digital data transmission at 1.25 Gbps. The BERT measurement unit was a Microwave Logic, Model gigaBERT. The oscilloscope signal for digital data received at 200 Mbps is shown in FIG. 3. At 1.25 Gbps, oscilloscope bandwidth limitations lead to the rounded bit edges seen in FIG. 4. Digital levels sustained for more than one bit period comprise

lower fundamental frequency components (less than 312 MHz) than those which toggle each period (622 MHz), so the modulation transfer function of the oscilloscope, which falls off above 500 MHz, attenuates them less. These measurement artifacts are not reflected in the bit error-rate measurements, which yield $<10^{-12}$ bit error rate at 1.25 Gbps.

Transceiver System

A preferred embodiment of the present invention is described by reference to FIGS. 5 to 7. The link hardware consists of a millimeter-wave transceiver pair including a pair of millimeter-wave antennas and a microwave transceiver pair including a pair of microwave antennas. The millimeter wave transmitter signal is amplitude modulated and single-sideband filtered, and includes a reduced-level carrier. The receiver includes a heterodyne mixer, phase-locked intermediate frequency (IF) tuner, and IF power detector.

*Rev. 6
9/15/04*
Millimeter-wave transceiver A (FIGS. 5A and 5B) transmits at 92.3-93.2 GHz as shown at 60 in FIG. 7A and receives at 94.1-95.0 GHz as shown at 62, while millimeter-wave transmitter B (FIGS. 6A and 6B) transmits at 94.1-95.0 GHz as shown at 64 in FIG. 7B and receives at 92.3-93.2 GHz as shown at 66.

Millimeter Wave Transceiver A

As shown in FIG. 5A in millimeter-wave transceiver A, transmit power is generated with a cavity-tuned Gunn diode 21 resonating at 93.15 GHz. This power is amplitude modulated using two balanced mixers in an image reject configuration 22, selecting the lower sideband only. The source 21 is modulated at 1.25 Gbps in conjunction with Gigabit-Ethernet standards. The modulating signal is brought in on optical fiber, converted to an electrical signal in media converter 19 (which in this case is an Agilent model HFCT-5912E) and amplified in preamplifier 20. The amplitude-modulated source is filtered in a 900 MHz-wide passband between 92.3 and 93.2 GHz, using a bandpass filter 23 on microstrip. A portion of the source oscillator signal is picked off with coupler 38 and combined with the lower sideband in power combiner 39, resulting in the transmitted spectrum shown at 60 in FIG. 7A. The combined signal propagates with

horizontal polarization through a wave guide 24 to one port of an orthomode transducer 25, and on to a two-foot diameter Cassegrain dish antenna 26, where it is transmitted into free space with horizontal polarization.

*Rev. 6
9/15/04*

The receiver unit at Station A as shown on FIGS. 5B1 and 5B2 is fed from the same Cassegrain antenna 26 as is used by the transmitter, at vertical polarization (orthogonal to that of the transmitter), through the other port of the orthomode transducer 25. The received signal is pre-filtered with bandpass filter 28A in a passband from 94.1 to 95.0 GHz, to reject back scattered return from the local transmitter. The filtered signal is then amplified with a monolithic MMW integrated-circuit amplifier 29 on indium phosphide, and filtered again in the same passband with bandpass filter 28B. This twice filtered signal is mixed with the transmitter source oscillator 21 using a heterodyne mixer-down converter 30, to an IF frequency of 1.00-1.85 GHz, giving the spectrum shown at 39A in FIG. 7A. A portion of the IF signal, picked off with coupler 40, is detected with integrating power detector 35 and fed to an automatic gain control circuit 36. The fixed-level IF output is passed to the next stage as shown in FIG. 5B2. Here a quadrature-based (I/Q) phase-locked synchronous detector circuit 31 is incorporated, locking on the carrier frequency of the remote source oscillator. The loop is controlled with a microprocessor 32 to minimize power in the "Q" channel while verifying power above a set threshold in the "I" channel. Both "I" and "Q" channels are lowpass-filtered at 200 MHz using lowpass filters 33A and 33B, and power is measured in both the "I" and "Q" channels using square-law diode detectors 34. The baseband mixer 38 output is pre-amplified and fed through a media converter 37, which modulates a laser diode source into a fiber-optic coupler for transition to optical fiber transmission media.

*Rev. 6
9/15/04*

Transceiver B

As shown in FIG. 6A in millimeter-wave transceiver B, transmit power is generated with a cavity-tuned Gunn diode 41 resonating at 94.15 GHz. This power is amplitude modulated using two balanced mixers in an image reject configuration 42, selecting the upper sideband only. The source 41 is modulated at 1.25 Gbps in conjunction with Gigabit-Ethernet standards. The modulating signal is brought in on optical fiber as

shown at 80, converted to an electrical signal in media converter 60, and amplified in preamplifier 61. The amplitude-modulated source is filtered in a 900 MHz-wide passband between 94.1 and 95.0 GHz, using a bandpass filter 43 on microstrip. A portion of the source oscillator signal is picked off with coupler 48 and combined with the higher side band in power combiner 49, resulting in the transmitted spectrum shown at 64 in FIG. 7B. The combined signal propagates with vertical polarization through a wave guide 44 to one port of an orthomode transducer 45, and on to a Cassegrain dish antenna 46, where it is transmitted into free space with vertical polarization.

(FIG. 6B1)

The receiver is fed from the same Cassegrain antenna 46 as the transmitter, at horizontal polarization (orthogonal to that of the transmitter), through the other port of the orthomode transducer 45. The received signal is filtered with bandpass filter 47A in a passband from 92.3 to 93.2 GHz, to reject backscattered return from the local transmitter. The filtered signal is then amplified with a monolithic MMW integrated-circuit amplifier on indium phosphide 48, and filtered again in the same passband with bandpass filter 47B. This twice filtered signal is mixed with the transmitter source oscillator 41 using a heterodyne mixer-downconverter 50, to an IF frequency of 1.00-1.85 GHz, giving the spectrum shown at 39B in FIG. 7B. A portion of the IF signal, picked off with coupler 62, is detected with integrating power detector 55 and fed to an automatic gain control circuit 56. The fixed-level IF output is passed to the next stage as shown on FIG. 6B2. Here a quadrature-based (I/Q) phase-locked synchronous detector circuit 51 is incorporated, locking on the carrier frequency of the remote source oscillator. The loop is controlled with a microprocessor 52 to minimize power in the "Q" channel while verifying power above a set threshold in the "I" channel. Both "I" and "Q" channels are lowpass-filtered at 200 MHz using a bandpass filters 53A and 53B, and power is measured in each channel using a square-law diode detector 54. The baseband mixer 58 output is pre-amplified and fed through a media converter 57, which modulates a laser diode source into a fiber-optic coupler for transition to optical fiber transmission media.

Very Narrow Beam Width

A dish antenna of two-foot diameter projects a half-power beam width of about 0.36 degrees at 94 GHz. The full-power beamwidth (to first nulls in antenna pattern) is narrower than 0.9 degrees. This suggests that up to 400 independent beams could be projected azimuthally around an equator from a single transmitter location, without mutual interference, from an array of 2-foot dishes. At a distance of ten miles, two receivers placed 800 feet apart can receive independent data channels from the same transmitter location. Conversely, two receivers in a single location can discriminate independent data channels from two transmitters ten miles away, even when the transmitters are as close as 800 feet apart. Larger dishes can be used for even more directivity.

Beam Steering

In the parent to this case Serial No. 09/847,692, the Applicants disclosed:

“Phased-array beam combining from several ports in the flat-panel phased array could steer the beam over many antenna beam widths without mechanically rotating the antenna itself. Sum-and-difference phase combining in a mono-pulse receiver configuration locates and locks on the proper “pipe.” In a Cassegrain antenna, a rotating, slightly unbalanced secondary (“conical scan”) could mechanically steer the beam without moving the large primary dish. For prime focus and offset parabolas, a multi-aperture (e.g., quad-cell) floating focus could be used with a selectable switching array. In these dish architectures, beam tracking is based upon maximizing signal power into the receiver. In all cases, the common aperture for the receiver and transmitter ensures that the transmitter, as well as the receiver, is correctly pointed.”

This Continuation-In-Part Application elaborates on this technique for keeping these pencil beams aligned.

Cassegrain Monopulse Tracking Antenna

In a preferred embodiment to provide end-user high-gain the antenna is a tracking Cassegrain antenna using monopulse tracking as shown in FIGS. 9, 10, and 11. FIG. 9 shows the principal elements of the antenna system. Cassegrain antenna 700 is utilized

with a four horn feed 702 which is a part of a monopulse tracking system 704 similar to monopulse tracking systems used for radar applications which are discussed in the Background section. The antenna system comprises a two-axis positioner 706 for the four horn feed which adjusts the four-horn feed in azimuth and elevation based on monopulse information as described below in order to keep it at all times pointed directly at a companion antenna with which it is communicating. As described below, communication (both transmit and receive) is through a four-horn sum signal that is provided to the four-horn feed 702.

FIG. 10 shows how signals are applied to and received from the four horns 702 to both communicate and to point the antenna beam. The positions of each of the four horns are shown at 708. ^(FIG. 10) The figure shows how the sum signals and the difference signals are extracted from the wave-guides feeding the horns. The figure also shows how an orthomode transceiver is used to both transmit and receive through the sum signal from the wave-guides.

FIG. 11 provides a more detailed layout of the monopulse tracking system. The system uses a single local oscillator 712, mixers 714, amplifiers 716, detectors 718 and automatic gain control 720 which is typical in monopulse radar tracking. The difference is the transmit signal is a digital communication signal in the range of about 92.3 to 93.2 GHz and the receive signal from its companion antenna is in the range of about 94.1 to 95.0 GHz as described above. The transmit and receive signals of its companion antenna are the reverse frequencies. The reader should refer to FIGS. 5A to 6B2 and the accompanying text for further details of the communication equipment for this system.

As is true for the planar phased array, when appropriate time delay is added to null out differential amplitude in the four receiver channels, a transmitter propagating source power back to the antenna through the same paths and delays is guaranteed to radiate out precisely toward the remote transceiver.

Other Tracking Dish Antennas

Other tracking techniques for keeping the pencil beam aligned can be used. One alternative is the conical scan technique that is another well known technique used for radar scanning. A good explanation of this scanning technique is provided in *Introduction to Radar Systems* by Merriss I Skolnik, McGraw-Hill, Pages 155-159. Those techniques for scanning the radar beam can be adapted to communication using the same techniques discussed above for the monopulse approach. Another approach is the sequential lobing also described in the above reference. It too could be adapted to keep the communication antennas aligned using the concepts described above.

In addition to the Cassegrain, other dish-type antennas could be used for tracking with the monopulse technique as described above. And these other types of antennas could also be used with the other scanning techniques. Some of these other antenna types are discussed below under the heading "Narrow Beam Width Antennas".

Backup Microwave Transceiver Pair

During severe weather conditions data transmission quality will deteriorate at millimeter wave frequencies. Therefore, in preferred embodiments of the present invention a backup communication link is provided which automatically goes into action whenever a predetermined drop-off in quality transmission is detected. A preferred backup system is a microwave transceiver pair operating in the 10.7-11.7 GHz band. This frequency band is already allocated by the FCC for fixed point-to-point operation. FCC service rules parcel the band into channels of 40-MHz maximum bandwidth, limiting the maximum data rate for digital transmissions to 45 Mbps full duplex. Transceivers offering this data rate within this band are available off-the-shelf from vendors such as Western Multiplex Corporation (Models Lynx DS-3, Tsunami 100BaseT), and DMC Stratex Networks (Model DXR700 and Altium 155). The digital radios are licensed under FCC Part 101 regulations. The microwave antennas are Cassegrain dish antennas of 24-inch diameter. At this diameter, the half-power beamwidth of the dish antenna is 3.0 degrees, and the full-power beamwidth is 7.4 degrees, so the risk of interference is higher than for MMW

antennas. To compensate this, the FCC allocates twelve separate transmit and twelve separate receive channels for spectrum coordination within the 10.7-11.7 GHz band.

Sensing of a millimeter wave link failure and switching to redundant microwave channel is an existing automated feature of the network routing switching hardware available off-the-shelf from vendors such as Cisco, Foundry Networks and Juniper Networks.

Narrow Beam Width Antennas

The narrow antenna beam widths afforded at millimeter-wave frequencies allow for geographical portioning of the airwaves, which is impossible at lower frequencies. This fact eliminates the need for band parceling (frequency sharing), and so enables wireless communications over a much larger bandwidth, and thus at much higher data rates, than were ever previously possible at lower RF frequencies.

The ability to manufacture and deploy antennas with beam widths narrow enough to ensure non-interference, requires mechanical tolerances, pointing accuracies, and electronic beam steering/tracking capabilities, which exceed the capabilities of the prior art in communications antennas. A preferred antenna for long-range communication at frequencies above 70 GHz has gain in excess of 50 dB, 100 times higher than direct-broadcast satellite dishes for the home, and 30 times higher than high-resolution weather radar antennas on aircraft. However, where interference is not a potential problem, antennas with dB gains of 40 to 45 may be preferred.

Most antennas used for high-gain applications utilize a large parabolic primary collector in one of a variety of geometries. The prime-focus antenna places the receiver directly at the focus of the parabola. The Cassegrain antenna places a convex hyperboloidal secondary reflector in front of the focus to reflect the focus back through an aperture in the primary to allow mounting the receiver behind the dish. (This is convenient since the dish is typically supported from behind as well.) The Grègorian antenna is similar to the Cassegrain antenna, except that the secondary mirror is a concave ellipsoid placed in back of the parabola's focus. An offset parabola rotates the focus away from the center of the dish for less aperture blockage and improved mounting geometry. Cassegrain,

prime focus, and offset parabolic antennas are the preferred dish geometries for the MMW communication system.

A preferred primary dish reflector is a conductive parabola. The preferred surface tolerance on the dish is about 15 thousandths of an inch (15 mils) for applications below 40 GHz, but closer to 5 mils for use at 94 GHz. Typical hydroformed aluminum dishes give 15-mil surface tolerances, although double-skinned laminates (using two aluminum layers surrounding a spacer layer) could improve this to 5 mils. The secondary reflector in the Cassegrainian geometry is a small, machined aluminum "lollipop" which can be made to 1-mil tolerance without difficulty. Mounts for secondary reflectors and receiver waveguide horns preferably comprise mechanical fine-tuning adjustment for in-situ alignment on an antenna test range.

Flat Panel Antenna

Another preferred antenna for long-range MMW communication is a flat-panel slot array antenna such as that described by one of the present inventors and others in U.S. Patent No. 6,037,908, issued 14 March 2000 which is hereby incorporated herein by reference. That antenna is a planar phased array antenna propagating a traveling wave through the radiating aperture in a transverse electromagnetic (TEM) mode. A communications antenna would comprise a variant of that antenna incorporating the planar phased array, but eliminating the frequency-scanning characteristics of the antenna in the prior art by adding a hybrid traveling-wave/corporate feed. Flat plates holding a 5-mil surface tolerance are substantially cheaper and easier to fabricate than parabolic surfaces. Planar slot arrays utilize circuit-board processing techniques (e.g. photolithography), which are inherently very precise, rather than expensive high-precision machining.

Typical Installation

FIG. 8 is a map layout of a proposed application of the present invention. This map depicts a sparsely populated section of the island, Maui in Hawaii. Shown are communication facility 70 which is connected to a major communication trunk line from a communication company's central office 71, a technology park 72 located about 2

2-26
7/10/84

561, 562
5A and 5B

miles from facility 70, a relay station 76 located about 6 miles from facility 70 and four large ocean-front hotels 78 located about 3 miles from relay station 76. Also shown is a mountaintop observatory 80 located 13 miles from facility 70 and a radio antenna tower 79 located 10 miles from facility 70. As indicated in FIG. 8, the angular separation between the radio antenna and the relay station is only 4.7 degrees. Four type-A transceiver units are positioned at facility 70, each comprising a transmitter and receiver unit as described in FIGS. 5A and 5B. These units are directed at corresponding type-B transceiver units positioned at the technology park, the relay station, the observatory, and the radio tower. Millimeter wave transceiver units with back-up microwave units as described above are also located at the hotels and are in communication with corresponding units at the relay station. In a preferred embodiment the 1.25 GHz spectrum is divided among the four hotels so that only one link needs to be provided between facility 70 and relay station 76. This system can be installed and operating within a period of about one month and providing the most modern communication links to these relatively isolated facilities. The cost of the system is a very small fraction of the cost of providing fiber optic links offering similar service.

The microwave backup links operate at approximately eight times lower frequency (8 times longer wavelength) than the millimeter wave link. Thus, at a given size, the microwave antennas have broader beam widths than the millimeter-wave antennas, again wider by about 8 times. A typical beam width from a 2-foot antenna is about 7.5 degrees. This angle is wider than the angular separation of four service customers (hotels) from the relay tower and it is wider than the angular separation of the beam between the relay station and the radio antenna. Specifically, the minimum angular separation between hotels from the relay station is 1.9 degrees. The angular separation between receivers at radio antenna tower 79 and relay station 76 is 4.7 degrees as seen from a transmitter at facility 70. Thus, these microwave beams cannot be separated spatially; however, the FCC Part 101 licensing rules mandate the use of twelve separate transmit and twelve separate receive channels within the microwave 10.7 to 11.7 GHz band, so these microwave beams can be separated spectrally. Thus, the FCC sponsored frequency coordination between the links to individual hotels and between the links to the relay

station and the radio antenna will guarantee non-interference, but at a much reduced data rate. The FCC has appointed a Band Manager, who oversees the combined spatial and frequency coordination during the licensing process.

Other Embodiments

Any millimeter-wave carrier frequency consistent with U.S. Federal Communications Commission spectrum allocations and service rules, including MMW bands currently allocated for fixed point-to-point services at 57-64 GHz, 71-76 GHz, 81-86 GHz, and 92-100 GHz, can be utilized in the practice of this invention. Likewise any of the several currently-allocated microwave bands, including 5.2-5.9 GHz, 5.9-6.9 GHz, 10.7-11.7 GHz, 17.7-19.7 GHz, and 21.2-23.6 GHz can be utilized for the backup link. The modulation bandwidth of both the MMW and microwave channels can be increased, limited again only by FCC spectrum allocations. Also, any flat, conformal, or shaped antenna capable of transmitting the modulated carrier over the link distance in a means consistent with FCC emissions regulations can be used. Horns, prime focus and offset parabolic dishes, and planar slot arrays are all included.

Transmit power may be generated with a Gunn diode source, an injection-locked amplifier or a MMW tube source resonating at the chosen carrier frequency or at any sub-harmonic of that frequency. Source power can be amplitude, frequency or phase modulated using a PIN switch, a mixer or a biphasic or continuous phase modulator. Modulation can take the form of simple bi-state AM modulation, or can involve more than two symbol states; e.g. using quantized amplitude modulation (QAM). Double-sideband (DSB), single-sideband (SSB) or vestigial sideband (VSB) techniques can be used to pass, suppress or reduce one AM sideband and thereby affect bandwidth efficiency. Phase or frequency modulation schemes can also be used, including simple FM, bi-phase, or quadrature phase-shift keying (QPSK). Transmission with a full or suppressed carrier can be used. Digital source modulation can be performed at any data rate in bits per second up to eight times the modulation bandwidth in Hertz, using suitable symbol transmission schemes. Analog modulation can also be performed. A monolithic or discrete-component power amplifier can be incorporated after the modulator to boost

the output power. Linear or circular polarization can be used in any combination with carrier frequencies to provide polarization and frequency diversity between transmitter and receiver channels. A pair of dishes can be used instead of a single dish to provide spatial diversity in a single transceiver as well.

The MMW Gunn diode and MMW amplifier can be made on indium phosphide, gallium arsenide, or metamorphic InP-on-GaAs. The MMW amplifier can be eliminated completely for short-range links. The detector can be made using silicon or gallium arsenide. The mixer/downconverter can be made on a monolithic integrated circuit or fabricated from discrete mixer diodes on doped silicon, gallium arsenide, or indium phosphide. The phase lock loop can use a microprocessor-controlled quadrature (I/Q) comparator or a scanning filter. The detector can be fabricated on silicon or gallium arsenide, or can comprise a heterostructure diode using indium antimonide.

The backup transceivers can use alternate bands 5.9-6.9 GHz, 17.7-19.7 GHz, or 21.2-23.6 GHz; all of which are covered under FCC Part 101 licensing regulations. The antennas can be Cassegrainian, offset or prime focus dishes, or flat panel slot array antennas, of any size appropriate to achieve suitable gain.

While the above description contains many specifications, the reader should not construe these as a limitation on the scope of the invention, but merely as exemplifications of preferred embodiments thereof. For example, the full allocated MMW band referred to in the description of the preferred embodiment described in detail above along with state of the art modulation schemes may permit transmittal of data at rates exceeding 10 Gbits per second. Such data rates would permit links compatible with 10-Gigabit Ethernet, a standard that is expected to become practical within the next two years. The present invention is especially useful in those locations where fiber optics communication is not available and the distances between communications sites are less than about 15 miles but longer than the distances that could be reasonably served with free space laser communication devices. Ranges of about 1 mile to about 10 miles are ideal for the

application of the present invention. However, in regions with mostly clear weather the system could provide good service to distances of 20 miles or more. Accordingly the reader is requested to determine the scope of the invention by the appended claims and their legal equivalents, and not by the examples given above.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000